



## HBNet FUNK-ZSU LI S.1/B.X ANTH MATT

85745285

### Functions

Power reserve	~ 24 h
<ul style="list-style-type: none"> <li>- ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display</li> <li>- reset function (to factory setting)</li> <li>- Configurable transmission and/or reception behaviour</li> <li>- Party function, no execution of automatic, radio and extension unit commands (switch protection)</li> <li>- with keylock</li> <li>- easy additional functions: +6 scenes, dimming, 1 up/down button control, priority</li> <li>- quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control</li> <li>- with switchover manual/automatic mode</li> </ul>	

### Controls and indicators

<ul style="list-style-type: none"> <li>- LC display illuminated during operation</li> <li>- indication of the application module/insert compatibility in the display</li> <li>- LC display contrast is adjustable</li> </ul>	
--	--

### Connectivity

Radio protocol	KNX Radio
----------------	-----------

### Frequency

Radio transmission/reception frequency	868,3 MHz
--	-----------

### Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

### Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
Running accuracy	± 3 min/year

### Materials

Colour of design line	anthracite
Surface appearance	matt

### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

- with automatic summer-/winter time switching (can be switched off)
- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- standalone programme, radio and extension unit commands are not executed
- holiday programme for random variation of the switching times in automatic operation

### Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20

- 2 independent preset programme memories, individually adaptable

### Use

- with display

### Safety

Protection index IP	IP20
---------------------	------

- with dismantling protection

### Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

### Identification

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Berker.Net, Berker S.1, Berker B.3, Berker B.7