



HBNet F-ZSU JAL S.1/B.x P-W GLÄ

85745189

Functions

Power reserve	~ 24 h
- ETS additional functions: +6 scenes, operating mode, status display, 2 x alarm - reset function (to factory setting) - with keylock - Party function, no execution of automatic, radio and extension unit commands (lock-out protection) - Configurable transmission and/or reception behaviour - easy additional functions: +6 scenes, 1 up/down operating mode - slat position storable for scene - scene opening via KNX radio appliances - quicklink functions for integration into the individual, group and master control of blinds/shutters - quicklink functions: blind, 2 scenes, forced control, up/down push-button - with switchover manual/automatic mode	

Controls and indicators

- indication of the application module/insert compatibility in the display - LC display contrast is adjustable - LC display illuminated during operation	
--	--

Connectivity

Radio protocol	KNX Radio
----------------	-----------

Frequency

Radio transmission/reception frequency	868,3 MHz
--	-----------

Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
Running accuracy	± 3 min/year

Detection

- sun protection and twilight-controlled lowering with radio brightness sensor

Materials

Colour of design line	polar white
Surface appearance	glossy

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

- with automatic summer-/winter time switching (can be switched off)
- astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
- standalone programme, radio and extension unit commands are not executed
- holiday programme for random variation of the operation times in automatic operation

Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
- 2 independent preset programme memories, individually adaptable	

Use

- with display

Safety

Protection index IP	IP20
- with dismantling protection	

Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

Identification

Application, usage	Blind control, KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Berker.Net, Berker B.3, Electronics platform, Berker S.1, Berker B.7

Instructions

- Can be switched to orientation led by extension unit.