



HBNet FW 2k S.1/B.X ANTH MATT

85656285

#### Functions

- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration button

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Frequency

Radio transmission frequency	868,3 MHz
------------------------------	-----------

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

- low intrinsic energy requirement

#### Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
--	-------------------------------

#### Battery

Battery service life [years]	~ 5
------------------------------	-----

- with lithium coin cell battery 3 V type: CR 2430

### Materials

RAL colour	RAL 7021 - Black grey
Colour of design line	anthracite
Material	thermoplastic
Surface appearance	matt

### Dimensions

Assembling height	14 mm
-------------------	-------

### LED control

- with configuration LED
- with transmission status and battery status LED, red/green/orange

### Installation, mounting

- for flat surface mounting and extension of combinations

### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

### Settings

- toolless quicklink configuration using buttons and LED display
- top and bottom operating areas are freely configurable

### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

### Safety

- with dismantling protection

### Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

### Identification

Application, usage	KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Berker.Net, Berker S.1, Berker B.7, Berker B.3