



## HBNet FW 2k SOLAR S1/BX P-W GLÄ

85656189

### Functions

- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
- reset function (to factory setting)
- easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
- quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

### Controls and indicators

- operating areas configurable as one or two-area operation
- with configuration button

### Connectivity

Radio protocol	KNX Radio
Receiver category	2

### Voltage

- power supply via solar cells

### Frequency

Radio transmission frequency	868,3 MHz
------------------------------	-----------

### Power

Radio transmission power	< 10 mW
--------------------------	---------

- low intrinsic energy requirement

### Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
--	-------------------------------

### Materials

RAL colour	RAL 9010 - Pure white
Colour of design line	polar white
Material	thermoplastic
Surface appearance	glossy

#### Dimensions

Assembling height	14 mm
-------------------	-------

#### LED control

- with configuration LED
- with transmission status LED, red/green/orange

#### Installation, mounting

- for flat surface mounting and extension of combinations

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

- toolless quicklink configuration using buttons and LED display
- top and bottom operating areas are freely configurable

#### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

#### Safety

- with dismantling protection

#### Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

#### Identification

Application, usage	KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Berker.Net, Berker S.1, Berker B.7, Berker B.3