



HBNet WÄCH F-QUICKL 2,2m K5 E-STAHL

85346173

Functions

- μ -processor controlled mode of operation
- ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value, brightness display, movement scene loading, no movement scene loading
- reset function (to factory setting)
- Party function for switching on for 2 hours
- with memory function for presence simulation
- with keylock
- Switch-off pre-warning on dimmer inserts
- Teach function for response brightness via button
- scene opening via KNX radio appliances
- scene saving lockable
- quicklink functions: switching, dimming, 2 scenes, time switching, NO contact push-button, Memory, forced control, Master-Slave

Compatibility

- optional operation of extension units using installation push-button

Controls and indicators

- remote control via quicklink transmitter
- with configuration and function button
- with button for on/off/automatic/memory/party function

Connectivity

Radio protocol	KNX Radio
Receiver category	2

Frequency

Radio transmission frequency	868,3 MHz
------------------------------	-----------

Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
Detection field, rectangular shaped	~ 8 x 12 m

Reach distance

Range, frontal	~ 8 m
Range, side	each ~ 6 m

Detection

Number of detection levels	2
Detection angle, settable	each side ~ 45 90 °

Materials

RAL colour	RAL 9022 - Pearl light grey
Colour of design line	stainless steel
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	matt

Dimensions

Assembling height	34 mm
Nominal mounting height	2,2 m

Lighting control

Response brightness, adjustable	~ 5 1000 lx , daytime operation
---------------------------------	---------------------------------

LED control

- LED application module/insert compatibility display
- with configuration and function LEDs
- with operation and status LED, red/green/orange

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

Response sensitivity, settable	10 100 %
Delay time, adjustable	~ 1 s 3 h
Switch-off pre-warning to dimming value 50% for	30 s

Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

Safety

- with dismantling protection

Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

Identification

Application, usage	Motion detector, KNX radio-sensors
Secondary design line(s)	Motion detector, Berker.Net, Berker K.5