



## SWITCH INSERT BLC TRIAC

2905

### Functions

- when cover is detached, the switch status is retained (wallpaper function)
- bulb-preserving soft startup

### Voltage

Operating voltage 230 V AC

### Fuse

- short-circuit and overload proof (fine-wire fuse)
- with spare fuse

### Measurement

- with extension unit input for BLC extension unit, BLC controller extension unit for motion detector and push-button, NO contact

### Materials

Colour not applicable  
Material Plastic/metal

### Incandescent bulbs control

230 V incandescent lamps and halogen lamps 40 400 W

### Installation, mounting

- with spreader claws

### Connection

- with screw terminals

---

**Equipment**

---

- phase cut-on

---

**Use conditions**

---

Operating temperature -20 45 °C

---

**Identification**

---

Application, usage	Radio bus - operating systems, Motion detector, Light control
--------------------	--

---

Main design line	Light control
------------------	---------------

---

Secondary design line(s)	Motion detector, Radio bus
--------------------------	----------------------------

---

**Instructions**

---

- Light scene function (On/Off) in conjunction with BLC radio button.
  - Possible to change fuse without removing cover.
-