



BLC relay switch insert

2906

Functions

- when cover is detached, the switch status is retained (wallpaper function)

Voltage

Operating voltage 230 V AC

Power

Conventional transformers	1000 VA
Electronic transformers	1500 W

Measurement

- with extension unit input for BLC extension unit, BLC controller extension unit for motion detector and push-button, NO contact

Materials

Colour	not applicable
Material	Plastic/metal

Dimensions

Insertion depth 22 mm

Fluorescent bulbs control

Fluorescent lamps in duo circuit	2300 VA
Fluorescent lamps parallel compensated	920 VA

Incandescent bulbs control

230 V incandescent lamps and halogen lamps	2300 W
--	--------

Installation, mounting

- with spreader claws

Connection

- with screw terminals

Equipment

- also usable as push-button relay switch

Use conditions

Operating temperature -20 45 °C

Identification

Application, usage	Light control, Motion detector, Radio bus - operating systems
Main design line	Light control
Secondary design line(s)	Motion detector, Radio bus

Instructions

- Light scene function (On/Off) in conjunction with BLC radio button.
