

Fus.-swi.-disconn. LT size 2 mon.pl. M10

LT250

### Architecture

Type of product	With safety switch disconnector
Number of poles	3 P
Type of pole	3 P
Controls and indicators	
With fault indicator	no
Main electrical features	
Frequency	50/60 Hz
Rated operational voltage Ue	0/690 V
Voltage	
Rated insulation voltage	1000 V
Overvoltage category according to IEC 60947-1 2.5.60 Table 1	IV-supply system level (feed)
Rated impulse withstand voltage	8000 V
Electric current	
Acceptable current rating with AC22 category B	400 A
Rated current for Ue=250V DC according to IEC 61439-1 5.3.2	400 A
Rated current for Ue=400V AC according to IEC 61439-1 5.3.2	400 A
Rated current for Ue=440V DC according to IEC 61439-1 5.3.2	400 A
Rated current for Ue=500V AC according to IEC 61439-1 5.3.2	400 A
Rated current for Ue=690V AC according to IEC 61439-1 5.3.2	400 A
Rating current of fuse cartridge	35/40/50/63/80/100/125/160/200/ 224/250/300/315/355/400 A
Rated short-time withstand current 1s	15,2 kA
Rated conditional short-circuit current for Ue=400V IEC 61439-1 3.8.10.4	80 kA
Rated conditional short-circuit current for Ue=500V IEC 61439-1 3.8.10.4	80 kA



Technical Properties	
Rated conditional short-circuit current for Ue=690V IEC 61439-1 3.8.10.4	80 kA
Fuse-links test rated cond. short-circuit current	400 A
Ue=400V IEC 61439-1 3.8.10.4	400 A
Fuse-links test rated cond. short-circuit current	400 A
Ue=500V IEC 61439-1 3.8.10.4	400 A
Fuse-links test rated cond. short-circuit current	400 A
Ue=690V IEC 61439-1 3.8.10.4	
Conv. free air therm.current w/fuse-links and std.	400 A
cross sect. IEC60947-1 4.3.2.1	
Conventional free air thermal current with	590 A
Trennmesser and std. cross section	
Electric current / temperature	
Rating current 40°C	400 A
Rating current 45°C	380 A
Rating current 50°C	360 A
Rating current 55°C	340 A
Rating current 60°C	320 A
Rating current 65°C	300 A
Rating current 70°C	280 A
Fuse	
CharactFuse	qG
Fuse Size	NH2
Power	
	126 W
Loss power at full load	~ 126 W
Loss power at full load  Maximum Power loss of the Fuse-Link installed in	~ 126 W 34 W
Loss power at full load  Maximum Power loss of the Fuse-Link installed in device	34 W
Loss power at full load  Maximum Power loss of the Fuse-Link installed in device  Total power loss under IN	· - · · ·
Loss power at full load  Maximum Power loss of the Fuse-Link installed in device	34 W 24,5 W
Loss power at full load  Maximum Power loss of the Fuse-Link installed in device  Total power loss under IN	34 W 24,5 W
Loss power at full load  Maximum Power loss of the Fuse-Link installed in device  Total power loss under IN  Dissipated energy in cable  Endurance	34 W 24,5 W 122 W
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance Electric endurance in number of cycles	34 W 24,5 W 122 W
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical	34 W 24,5 W 122 W
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical	34 W 24,5 W 122 W
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions	34 W 24,5 W 122 W 200 1000 800
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product	34 W 24,5 W 122 W 200 1000
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product  Height of installed product	34 W 24,5 W 122 W  200 1000 800  1003 g
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product	34 W 24,5 W 122 W 200 1000 800 1003 g
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product Height of installed product Width of installed product	34 W 24,5 W 122 W  200 1000 800  1003 g
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product  Height of installed product	34 W 24,5 W 122 W  200 1000 800  1003 g
Loss power at full load Maximum Power loss of the Fuse-Link installed in device Total power loss under IN Dissipated energy in cable  Endurance  Electric endurance in number of cycles Total service life (mechanical and electrical endurance) IEC 60947-3 Table 4 Number of mechanical operations  Materials  Copper weight of the product  Dimensions  Depth of installed product Height of installed product Width of installed product	34 W 24,5 W 122 W  200 1000 800  1003 g

_				
1,0	nn	~~	***	١m
Co	'1111	ヒし	uv	"

Standards	
Terminal type of the outputs	Connexion with screv
Input connection type	Connexion with screw
Connection cross-sect. flexible conductor	70 / 300mm²
Connection cross-sect. rigid cable	70 / 300mm²

Degree of protection (NEMA)	1
Operation of switching devices according to IEC 60947-1 2.4	depending manual operation (of a mechanical switching device)
Rated duties according to IEC 60947-1 4.3.4	Continuous operation
Standard cross section according to IEC 60947-1 Tables 9 and 10	240 mm²
Utilisation category for Ue=250V DC according to IEC 60947-3 Table 5	DC-22B
Utilisation category for Ue=400V AC according to IEC 60947-3 Table 5	AC-23B
Utilisation category for Ue=440V DC according to IEC 60947-3 Table 5	DC-21B
111111 11 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	4.0.000

60947-3 Table 5	
Utilisation category for Ue=500V AC according to IEC	AC-23B
60947-3 Table 5	
Utilisation category for Ue=690V AC according to IEC	AC-22B
60947-3 Table 5	
European directive WEEE	concerned

# Safety

Protection index IP	IP3X

# Use conditions

Degree of pollution according to IEC 60664 / IEC	3
60947-2	
Storage temperature	-40 to 70 °C

### temperatur

Max. temperature connected above with Fuse-Links IEC 60947-1 Tab 2	65 K
Max. temperature connected above with Solid-links IEC 60947-1 Table 2	64,5 K
Max. temperature connected below with Fuse-Links IEC 60947-1 Table 2	49 K
Max. temperature connected below with Solid-links IEC 60947-1 Table 2	55 K

# Weight

Weight	3,2 kg