



Touch dimmer (R, L), Electronics platf.

85421100

Functions

- bulb-preserving soft startup

Voltage

Operating voltage 230 V AC

Fuse

- short-circuit and overload proof (electronic fuse)

Power

Power consumption (standby) < 0,3 W

- low intrinsic energy requirement

Measurement

Relative humidity (without condensation) 0 65 % (without condensation)

- with extension unit input for push-button (NO contact), single-surface operation and motion detector extension unit

Materials

Colour not applicable

Material Plastic/metal

- no conductive connection between supporting ring and spreading claws

Dimensions

Insertion depth 32 mm

Incandescent bulbs control

230 V incandescent lamps and halogen lamps 25 400 W

Installation, mounting

- with spreader claws

Connection

- with screw terminals

Equipment

- switch-on brightness level can be stored safe after power failure
- phase cut-on

Use conditions

Operating temperature -5 45 °C

Identification

Application, usage	Motion detector, KNX radio-operating systems, Light control
Main design line	Electronics platform