



## HBNet F-TA 1k JAL K5 E-STAHL

Similar image  
(Picture shows 85245273)

### Functions

---

- ETS additional functions: +6 scenes, operating mode, status display, 2 x alarm
  - Party function, no execution of automatic, radio and extension unit commands (lock-out protection)
  - Configurable transmission and/or reception behaviour
  - Memory function for automatic execution of learned up and down times with position
  - reset function (to factory setting)
  - easy additional functions: +6 scenes, 1 up/down operating mode
  - slat position storable for scene
  - scene opening via KNX radio appliances
  - quicklink functions: blind, 2 scenes, memory, forced control, up/down push-button
- 

### Controls and indicators

---

- activation of the party function using buttons in up and down direction > 20 sec.
  - with configuration and function button
- 

### Connectivity

---

|                |           |
|----------------|-----------|
| Radio protocol | KNX Radio |
|----------------|-----------|

---

### Frequency

---

|  |           |
|--|-----------|
| Radio transmission/reception frequency | 868,3 MHz |
|--|-----------|

---

### Power

---

|                          |         |
|--------------------------|---------|
| Radio transmission power | < 10 mW |
|--------------------------|---------|

---

- low intrinsic energy requirement
- 

### Measurement

---

|  |                               |
|--|-------------------------------|
| Relative humidity (without condensation) | 0 65 % (without condensation) |
|--|-------------------------------|

---

### Detection

---

- sun protection and twilight-controlled lowering with radio brightness sensor
-

#### Materials

|                        |                             |
|------------------------|-----------------------------|
| RAL colour             | RAL 9022 - Pearl light grey |
| Colour of design line  | stainless steel             |
| Material / workmanship | lacquered                   |
| Material               | thermoplastic               |
| Surface appearance     | matt                        |

#### LED control

- with status LED for memory and party function, red/orange
- with configuration and function LEDs
- with indicator LED for lock-out protection
- LED application module/insert compatibility display

#### Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

#### Settings

- toolless quicklink configuration using buttons and LED display

#### Equipment

|                           |                              |
|---------------------------|------------------------------|
| Number of radio channels  | 1                            |
| Number of quicklink links | max. 20 transmitter/receiver |

#### Safety

- with dismantling protection

#### Use conditions

|                       |          |
|-----------------------|----------|
| Operating temperature | -5 45 °C |
|-----------------------|----------|

#### Identification

|                          |   |
|--------------------------|---|
| Application, usage       | Blind control, KNX radio- operating systems |
| Secondary design line(s) | Electronics platform, Berker K.5            |