



HBNet FUNK-ZSU LI R.1 P-W GLÄ

85745239

Functions

Power reserve	~ 24 h
<ul style="list-style-type: none"> - ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display - reset function (to factory setting) - Configurable transmission and/or reception behaviour - Party function, no execution of automatic, radio and extension unit commands (switch protection) - with keylock - easy additional functions: +6 scenes, dimming, 1 up/down button control, priority - quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control - with switchover manual/automatic mode 	

Controls and indicators

<ul style="list-style-type: none"> - LC display illuminated during operation - indication of the application module/insert compatibility in the display - LC display contrast is adjustable 	
--	--

Connectivity

Radio protocol	KNX Radio
----------------	-----------

Frequency

Radio transmission/reception frequency	868,3 MHz
--	-----------

Power

Radio transmission power	< 10 mW
- low intrinsic energy requirement	

Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
Running accuracy	± 3 min/year

Materials

Colour of design line	polar white
Surface appearance	glossy

Connection

- integration in the KNX radio/TP gateway, surface-mounted, into the KNX TP system

Settings

-
- with automatic summer-/winter time switching (can be switched off)
 - astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
 - standalone programme, radio and extension unit commands are not executed
 - holiday programme for random variation of the switching times in automatic operation
-

Equipment

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20

- 2 independent preset programme memories, individually adaptable

Use

-
- with display
-

Safety

Protection index IP	IP20
---------------------	------

- with dismantling protection

Use conditions

Operating temperature	-5 45 °C
-----------------------	----------

Identification

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker R.1/R.3/Serie 1930/R.classic
Secondary design line(s)	Electronics platform, Berker R.1, Berker R.3, Serie 1930, Series R.classic

Instructions

-
- Note:
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!
-