



HBNet ZSU JAL R.1 P-W GLÄ

85741139

Functions

Power reserve	~ 24 h
- reset function (to factory setting)	
- with keylock	
- Party function, no execution of automatic, radio and extension unit commands (lock-out protection)	
- with switchover manual/automatic mode	

Controls and indicators

- LC display illuminated during operation
- indication of the application module/insert compatibility in the display
- LC display contrast is adjustable

Power

- low intrinsic energy requirement

Measurement

Relative humidity (without condensation)	0 65 % (without condensation)
--	-------------------------------

Detection

- Not suitable for rain and wind sensors

Materials

Colour of design line	polar white
Colour	polarwhite
Material	Plastic/metal

Installation, mounting

- clamp fastening

Settings

- with automatic summer-/winter time switching (can be switched off)
 - astro programme for sunrise/sundown switching with city/country or co-ordinate input, individually adaptable
 - holiday programme for random variation of the operation times in automatic operation
-

Equipment

- 2 independent preset programme memories, individually adaptable
-

Use

- with display
-

Safety

- with dismantling protection
-

Use conditions

Operating temperature -5 45 °C

Identification

Application, usage	Blind control
Main design line	Berker R.1/R.3/Serie 1930/R.classic
Secondary design line(s)	Berker R.3, Berker R.1

Instructions

- Note:
When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!
 - Can be switched to orientation led by extension unit.
-